

ASUS PRIME A520M-E/CSM AMD A520 Socket AM4 micro ATX

Brand : ASUS

Product code: 90MB1510-M0EAYC

Product name : PRIME A520M-E/CSM

- AMD AM4 socket: Ready for Ryzen™ 5000 Series/ 4000 G-Series/ 3000 Series Desktop Processors
 - Comprehensive cooling: PCH heatsink and Fan Xpert
 - Ultrafast connectivity: M.2 support, 1 Gb Ethernet, USB 3.2 Gen 2 Type-A
 - 5X Protection III: Multiple hardware safeguards for all-around system protection
 AMD A520, AMD AM4, 2 x DIMM, Max. 64GB, DDR4, 256 Mb Flash ROM, UEFI AMI BIOS, mATX
 ASUS PRIME A520M-E/CSM. Processor manufacturer: AMD, Processor socket: Socket AM4, Compatible processor series: AMD Ryzen™ 3, AMD Ryzen™ 5, AMD Ryzen™ 7. Supported memory types: DDR4-SDRAM, Maximum internal memory: 64 GB, Memory slots type: DIMM. Supported storage drive interfaces: M.2, SATA III, Supported storage drive types: HDD & SSD, RAID levels: 0, 1, 10. Ethernet interface type: Fast Ethernet, Gigabit Ethernet, LAN controller: Realtek RTL8111H. Component for: PC, Motherboard form factor: micro ATX, Motherboard chipset family: AMD



Processor		Internal I/O	
Processor manufacturer *	AMD	Number of COM connectors	1
Processor socket *	Socket AM4	TPM connector	✓
Compatible processor series *	AMD Ryzen™ 3, AMD Ryzen™ 5, AMD Ryzen™ 7	Rear panel I/O ports	
Memory Supported memory types * Number of memory slots * Memory slots type Memory channels ECC compatibility Supported memory clock speeds Maximum internal memory * Unbuffered memory	DDR4-SDRAM	USB 2.0 ports quantity *	2
	2	USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	4
	DIMM	USB 3.2 Gen 2 (3.1 Gen 2) Type-A ports quantity *	1
	Dual-channel	Ethernet LAN (RJ-45) ports *	1
	ECC	PS/2 ports quantity	1
	2133,2400,2666,2800,2933,3000,3200,3333,3400,3466,3600,3733,3866,4000,4133,4200,4266,4333,4400,4466,4600,4866	VGA (D-Sub) ports quantity *	1
	MHz	HDMI ports quantity *	1
	64 GB	DVI-D ports quantity *	1
	✓	Network	
Storage controllers		Ethernet LAN	✓
Supported storage drive types	HDD & SSD	Ethernet interface type	Fast Ethernet, Gigabit Ethernet
Supported storage drive interfaces *	M.2, SATA III	LAN controller	Realtek RTL8111H
Number of HDDs supported	4	Wi-Fi *	✗
Number of storage drives supported	5	Features	
RAID support	✓	Motherboard chipset *	AMD A520
RAID levels	0, 1, 10	Audio output channels *	7.1 channels
Internal I/O		Component for *	PC
USB 2.0 connectors *	2	Motherboard form factor *	micro ATX
USB 3.2 Gen 1 (3.1 Gen 1) connectors *	1	Motherboard chipset family *	AMD
Number of SATA III connectors *	4	Windows operating systems supported	Windows 10 x64
S/PDIF out connector	✓		
Front panel audio connector	✓		
ATX Power connector (24-pin)	✓		
CPU fan connector	✓		
Number of chassis fan connectors	1		

Internal I/O		Expansion slots	
EPS power connector (8-pin)	✓	PCI Express x1 (Gen 3.x) slots	2
		Number of M.2 (M) slots	1
BIOS			
		BIOS type *	UEFI AMI
		BIOS memory size	256 Mbit
Weight & dimensions			
		Width	226 mm
		Depth	221 mm



4718017826396

Catalog Object Cloud



Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity. Automated scraping, data mining, or harvesting for the purpose of training machine learning models, neural networks, or artificial intelligence systems is strictly prohibited without a commercial license.